

Emergency Ballasts/ Under Cabinet Lights

FLUORESCENT EMERGENCY LIGHTING BALLASTS

- 120/277 VAC, Fully Automatic Operation
- 280mA Charging current
- 24Hr Recharging Time
- 90 minutes of emergency operation
- Wireway or Fixture Mount
- Battery, Charger, Inverter Circuit in a Single Package
- **For more information see page F18**



BAL650C



BAL500



BAL700









BAL1400



BAL3000

FLUORESCENT EMERGENCY LIGHTING BALLASTS LAMP COMPATIBILITY CHART

For more information see page F19

Cat. No.	Description
BAL650C-2PIN	For 2-Pin Compact Fluorescent Lamp Operates One 13W - 42W or Two 13W - 39W Twin, Quad Lamps 
BAL650C-4PIN	For 4-Pin Compact Fluorescent Lamp Operates One 13W - 42W or Two 13W - 39W Twin, Quad, Triple-Twin, Long Compact or 2D Lamps 
BAL500	Operates One 17W - 40W (2' - 4') T8, T10, or T12 Lamp 
BAL700	Operates One 17W - 215W (2' - 8'), or Two 17W - 40W (2' - 4') T8, T9, T10, or T12 Lamps 
BAL1400	Operates One 17W - 215W (2' - 8'), or Two 17W - 40W (2' - 4') T8, T9, T10, or T12 Lamps 
BAL3000	Operates One of: F025, FB024 T8, F032, FB031 T8, F096 T8, F017, FB016, F40T12, F40/U, F48T12/HO, F96T12, HO, VHO  Or Two of: F025, FB024 T8, F032, FB031 T8, F017, FB016, F40T12, F40/U

UNDER CABINET LIGHTS

- 120~125 VAC
- T5 Fluorescent Lamp
- Electronic Class P Ballast
- Turn Switch Included
- Heavy Gage Steel with Flush Ends
- K.O.s on Top, Sides, and Back
- Baked white enamel
- With Rust Inhibiting Phosphate Coat
- **For more information see page F20**



UCL-12



UCL-21



UCL-24



UCL-33



UCL-42