



Catalog#: 4M3-4S

4" SQUARE RING ADAPTER FOR 3-GANG BOX

Category SWITCH BOX
Page [A27](#)
Barcode 8-35243-02851-7

Description:

Orbit Industries' 4" Square Ring Adapter for 3-Gang Junction Box transitions a multigang box into a 4" square opening. Ideal for construction markets where 2-1/2" stud depths are common. Increase box fill volume by 55% (65 Cu. In.) versus deep 4-11/16" Sq. junction boxes (42 Cu. In.). Increased volume allows for more conductors and fittings within tight wall spaces. 4M3-4S is designed for use with 3-Gang Junction Boxes ([SB-3](#)). For New Construction and Retrofit applications.

Features:

- Ideal where 2-1/2" stud depths are common
- Compatible with any style of 4" square device rings, including adjustable depth models
- Increase box fill volume by 55% (up to 65 Cu. In.) versus deep 4-11/16" Sq. junction boxes (42 Cu. In.)
- Designed for use with shallow (1-5/8" Deep) 3-Gang Outlet Boxes ([SB-3](#))

Dimensions:

Width	8 - 5/8"
Height	4 - 9/16"
No. of Gangs	3

Specifications:

Material	16 GA Sheet Steel
Color	Galvanized

Packaging Info:

Std Pkg	25
---------	----

Certifications:

